

# SmartBirght LED Batten

## BN013C

### Mounting Instruction

	AS/NZS 60598	220V 240V	50Hz 60Hz		$t_a 25^{\circ}\text{C}$	IP20			
--	--------------	--------------	--------------	--	--------------------------	------	--	--	--

Product Type	Dimension (mm)	CCT (K)	Lumen Output (lm)	Power (W)	light source of energy efficiency class	
BN013C LED20/WW L1200 AU G3	1186×28.4×35.7	3000	1900	20	E	0.17
BN013C LED20/NW L1200 AU G3	1186×28.4×35.7	4000	2000	20	D	0.17
BN013C LED20/CW L1200 AU G3	1186×28.4×35.7	6500	2000	20	D	0.17
BN013C LED10/WW L600 AU G3	586×28.4×35.7	3000	950	10	E	0.09
BN013C LED10/NW L600 AU G3	586×28.4×35.7	4000	1000	10	D	0.09
BN013C LED10/CW L600 AU G3	586×28.4×35.7	6500	1000	10	D	0.09

Unit: mm

Inrush Current		
	Ipeak	T(@50% of Ipeak)
20W	14.3A	1 μs
10W	9A	1 μs

### Surface Mounting

Installation on ceiling or wall through mounting clips.

D: Mounting distance

Type	L600	L1200
D (mm)	300-500	600-800

Unit: mm

#### Trunking method A

Click fit male plug part into female socket. Affix next system, only after linking. Maximum amount of linking: 10pcs

#### Trunking method B

Use connector jack cable (Not provided in this pack) for linking, as required. Maximum amount of linking: 10pcs  
L-Linkable cable : ZCH086 L265

#### Wire Connection

Use 2 pin plug\* for power connection. \* 2 pin plug is not provided. Power cable : ZCH086 L 1200

Signify Luminaires (Shanghai) Co., Ltd.  
 Address: 2F, Building 6, No. 1805, Huiyi Highway, Malu Town, Jiading District, Shanghai, P.R. China  
 Postal code: 201801









# SmartBirght LED Batten

BN013C

## Mounting Instruction

Please read this manual carefully before using the product.

1. For indoor use only.
2. Do not switch on before complete installation.
3. The luminaire must be installed by a licensed electrician and wired in accordance with Australian wiring rules.
4. The external flexible cable or cord of this luminaire cannot be replaced; if the cord is damaged, the luminaire shall be destroyed.
5. The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced.
6. The luminaire is complied with AS/NZS 60598.
7. Luminaire must not be used or stored in corrosive environment where hazardous materials such as Sulphur, Chlorine, phthalates, etc., are present.
8. This product allows maximum 10 pcs trunking (via connector or end to end trunking). For your safety concern, the connection of BN013C with any other product is prohibited. And make sure to keep the last male socket open.
9. Max current of power cable: 2A.



This marking indicates that this product should not be disposed with other household wastes throughout the EU. To prevent possible harm to the environment or human health from uncontrolled waste disposal, recycle it responsibly to promote the sustainable reuse of material resources. To return your used device, please use the return and collection systems or contact the retailer where the product was purchased. They can take this product for environmental safe recycling.

# PHILIPS

Philips and the Philips shield emblem are registered trademarks of Koninklijke Philips N.V.